

**PLC Splitter**

**Tray Type PLC Splitter**



**DESCRIPTION**

ANDA TELECOM PLC splitter is based on silicon dioxide waveguides, which is used to connect main equipment and terminal equipment in EPON, BPON and GPON network.

**FEATURES**

- Qualified with CE certificate and ROHS certificate.
- Comply with GR-1209-CORE, GR-1221-CORE, YD/T 2000.1-2014 and IEC criterion.

**HOUSING SIZE AND RIBBION:**

**T3.1 Tray type PLC Splitter dimension**

Dimension	nx2, nx4, nx8, nX16	1X32, 2X32	1X64, 2X64
L x W x H (mm)	288×180×25	288×180×50	288×180×100

**ANDA Telecom Pvt. Ltd.**

Registered office: E-36, Amar Colony, Lajpat Nagar-IV, New Delhi - 110024, INDIA

Phone: +91 11 41323629, +91 95 302 57173

E-mail: [Info@andatelecomindia.com](mailto:Info@andatelecomindia.com)

URL: [www.andatelecomindia.com](http://www.andatelecomindia.com)

**OPTICAL PARAMETER:**

**T4.1 1×N (N≥2) PLC splitter optical parameter**

Parameter		1X2	1x4	1x8	1x16	1x32	1x64
Wavelength (nm)		1260 ~ 1650					
IL (dB)		≤4.1	≤7.4	≤10.5	≤13.8	≤17.1	≤20.4
Uniformity (dB)		≤0.6	≤0.7	≤0.8	≤1.0	≤1.5	≤2.0
RL (dB)		≥50(PC); ≥55(APC)					
PDL (dB)		≤0.15	≤0.2	≤0.2	≤0.3	≤0.3	≤0.3
Directivity (dB)		≥55	≥55	≥55	≥55	≥55	≥55
Environ ment	Operating temp(°C)	-40~85°C					
	Storage temp(°C)	-40~85°C					
	Humidity	≤95% (+40°C)					
	Atmospheric pressure	62~106kPa					
Fiber		SM G657A or customized					
Connector		SC, FC, LC					
Pigtail (mm)		1000, 1500, 2000 or customized					

**T4.2 2×N (N≥2) PLC splitter optical parameter**

Parameter		2X2	2x4	2x8	2x16	2x32	2x64
Wavelength (nm)		1260 ~ 1650					
IL (dB)		≤4.4	≤7.7	≤10.8	≤14.1	≤17.4	≤20.7
Uniformity (dB)		≤0.8	≤1.0	≤1.0	≤1.5	≤1.8	≤2.0
RL (dB)		≥50(PC); ≥55(APC)					
PDL (dB)		≤0.2	≤0.2	≤0.3	≤0.3	≤0.3	≤0.4
Directivity (dB)		≥55	≥55	≥55	≥55	≥55	≥55
Environ	Operating temp(°C)	-40~85°C					
	Storage temp(°C)	-40~85°C					
	Humidity	≤95% (+40°C)					

**ANDA Telecom Pvt. Ltd.**

Registered office: E-36, Amar Colony, Lajpat Nagar-IV, New Delhi - 110024, INDIA

Phone: +91 11 41323629, +91 95 302 57173

E-mail: [Info@andatelecomindia.com](mailto:Info@andatelecomindia.com)

URL: [www.andatelecomindia.com](http://www.andatelecomindia.com)



Turning Copper into Gold

ment	Atmospheric pressure	62~106kPa
	Fiber	SM G657A or customized
	Connector	SC, FC, LC
	Pigtail (mm)	1000, 1500, 2000 or customized

**ANDA Telecom Pvt. Ltd.**

Registered office: E-36, Amar Colony, Lajpat Nagar-IV, New Delhi - 110024, INDIA

Phone: +91 11 41323629, +91 95 302 57173

E-mail: [Info@andatelecomindia.com](mailto:Info@andatelecomindia.com)

URL: [www.andatelecomindia.com](http://www.andatelecomindia.com)