



Turning Copper into Gold

AT-OFS-95R Ribbon Fiber Fusion Splicer uses high-speed image processing technology and high-precision V-groove precision positioning technology, which can make the optical fiber fast with automatic fusion and has high-quality fusion effect. The 5-inch LCD and dual CMOS monitors are perfectly matched, and the X- axis and Y-axis can be displayed simultaneously or separately. OFS-95R is suitable for the construction, maintenance and repair of ribbon cables. It supports multimode fiber (MMF / G.651), single mode fiber (SMF / G.652), dispersion-shifted fiber (DSF / G.653) and non-zero Dispersion-shifted fiber (NZ-DSF / G.655), bend- insensitive fiber (BIF / G.657) and other fibers.



AT-OFS-95R

ANDA Telecom Pvt. Ltd.

Registered office : E-36, Amar Colony, Lajpat Nagar-IV, New Delhi -
110024, INDIA Phone : +91 11 41323629, +91 95 302 57173

E-mail : Info@andatelecomindia.com

URL : www.andatelecomindia.com

Features

- ◆ Compact and light: 1.8Kg with battery
- ◆ SMF (G.652), MMF (G.651), DSF (G.653), NZ-DSF (G.655), BIF (G.657), EDF splicing
- ◆ Auto fiber end-face inspection, auto arc position adjustment, splice loss calculation, temperature and pressure compensation
- ◆ Auto and manual splicing
- ◆ Splicing ≤ 15 second, heating ≤ 25 second (time and power adjustable)
- ◆ Arc counter prompts electrode change upon usage
- ◆ Auto arc optimization
- ◆ Auto heating
- ◆ X/Y and X+Y display for clear fiber core image
- ◆ Quick mount battery with power indicator, housed in dust and water splash proof batterydock
- ◆ DC output to power external devices
- ◆ Built-in illumination
- ◆ Wind – dust – rain - shock proof
- ◆ Auto display flip
- ◆ Graphical user interface for easy understanding and operation
- ◆ Multi-language support

Specifications

Model	AT-OFS-95R
Fiber Type	SMF (G.652), MMF (G.651), DSF (G.653), NZ-DSF (G.655), BIF (G.657), EDF
Protection Sleeve	40mm - 60mm
Splicing Principle	Arc
Number of Fiber Cores	1、 2、 4、 6、 8、 10、 12
Splice Control	Auto and Manual Splicing
Arc Optimization	Yes
Display Mode	X, Y, X+Y
User Interface	Graphical interface, multiple language support
Splice Result	Auto Splice Result (Loss) Calculation and Display
Data	5000 Splice Records (CSV Format), 100 Screenshots
Data Port	USB, Driver-free
Fiber Diameter	Cladding: 80~150 μ m, Coating: 100~1000 μ m
Cleave Length	10mm~13mm

ANANDA Telecom Pvt. Ltd.

Registered office : E-36, Amar Colony, Lajpat Nagar-IV, New Delhi - 110024,
INDIA Phone : +91 11 41323629, +91 95 302 57173

E-mail : Info@andatelecomindia.com

URL : www.andatelecomindia.com

Splice Loss	MMF \leq 0.02dB (Typical); SMF/BIF \leq 0.05dB (Typical); DSF/NZDSF/EDF \leq 0.08dB (Typical)
Return Loss	> 60dB
Splice Time	\leq 15s
Heating Time	\leq 25s, Adjustable
Zoom	20x ~ 50x
Electrode Life	\geq 3000 Splices
Tension Test	\geq 2N
Start-up Time	7s
Power Supply	220V \pm 10%, 50Hz; Rechargeable Lithium Battery
Battery Life	\geq 100 Splicing and Heating
Charging Time	\leq 4 Hours
Size	125x125x135mm (L x W x H)
Weight	1.8Kg (With Battery)
Work Temperature	-20°C ~ +55°C
Storage Temperature	-40°C ~ +70°C
Humidity	\leq 95% (Non-condensing)
Altitude	0 m ~ 3000 m
Wind Speed	\leq 15 m/s

Configuration

Splicer Unit x 1, Fiber Holder x 1 (Pair), Lithium Battery x 1, PowerAdapter x 1, Fiber Cleaver x 1, Cooling Tray x 1, USB Cable x 1, Carry Case x 1, Quick Reference